

Speeds & Feeds

Product Table: Back Deburring Mill **Characteristics:** 12x Reach Multiple **Series:** 570xx, 571xx

Product Notes:

When selecting Chip Loads (IPT) by diameter, please be sure to consider the <u>Effective Cutter Diameter</u> (D4 dimension in catalog) This should not be confused with the Head Diameter.

Chip Loads are given 2 ways: Deburring refers to removing the burr only Edge Break refers to a .002" -.005" chamfered feature on the workpiece

Chip Loads (IPT) within table reflect machining on 1 side of existing feature For machining on 2 sides, reduce Chip Load to 60% of posted values

When machining using Circular Interpolation, the Linear Feed rate (IPM) should be adjusted

For Circular Interpolation around inside of a hole: Adjusted Feed = [(Major Diameter - Effective Cutter Diameter) / Major Diameter] x Linear Feed For Circular Interpolation around outside of post: Adjusted Feed = [(Major Diameter + Effective Cutter Diameter) / Major Diameter] x Linear Feed

| Material | Hardness | SFM | STARTING CHIP LOAD (IPT) By EFFECTIVE CUTTER DIAMETER | | | | | | | | | | | | |
|--------------------|------------|------------|---|--------|--------|--------|--------|--------|--------|--------|--------|--------|--------|--------|--------|
| | | | | .015 | .031 | .047 | .062 | .078 | .093 | .125 | .187 | .250 | .312 | .375 | .500 |
| Non-Ferrous Alloys | ≤ 28 Rc | 200 - 1200 | Deburr | .00005 | .00012 | .00018 | .00023 | .00029 | .00042 | .00056 | .00084 | .00113 | .00141 | .00169 | .00226 |
| | | | Edge Break | .00004 | .00010 | .00015 | .00020 | .00025 | .00036 | .00048 | .00072 | .00096 | .00120 | .00144 | .00193 |
| Ferrous Alloys | ≤ 45 Rc | 150 - 250 | Deburr | .00004 | .00010 | .00016 | .00021 | .00026 | .00038 | .00051 | .00076 | .00101 | .00127 | .00152 | .00203 |
| | | | Edge Break | .00003 | .00009 | .00014 | .00018 | .00022 | .00032 | .00043 | .00065 | .00087 | .00108 | .00130 | .00173 |
| | 46 < 68 Rc | 50 - 100 | Deburr | .00004 | .00009 | .00014 | .00019 | .00023 | .00034 | .00045 | .00067 | .00090 | .00113 | .00135 | .00180 |
| | | | Edge Break | .00003 | .00008 | .00012 | .00016 | .00020 | .00029 | .00039 | .00058 | .00077 | .00096 | .00116 | .00154 |

General Notes:

All posted speed and feed parameters are suggested starting values that may be increased given optimal setup conditions. Chip loads reflect uncoated cutters and may be increased 10%-20% if coated.

If you require additional information, Harvey Tool has a team of technical experts available to assist you through even the most challenging applications. Please contact us at **800-645-5609** or **Harveytech@harveyperformance.com**.

WARNING: Cutting tools may shatter under improper use. Government regulations require use of safety glasses and other appropriate safety equipment in the vicinity of use.